

# PRO 1000

## Multi-Connector System / Coaxial Adapter Kit

### DESCRIPTION

- Make your own coaxial adapters with the PRO 1000 kit.
- 136 different combinations possible.
- Save time and money.
- Easy and fast connection between different coaxial connectors.
- Contains N-, UHF-, MUHF-, BNC-, TNC-, SMA-, F- and Phono-connectors.
- Gold plated brass and teflon insulation for optimum electrical performance.
- Indispensable in every radio workshop.
- Delivered in handy and protective soft case.



### ORDERING DESIGNATIONS

TYPE	PRODUCT NO.
PRO 1000	130000590

### SPECIFICATIONS

ELECTRICAL	
MODEL	PRO 1000
APPLICATION	Coaxial adaptor kit (N to BNC, TNC to SMA, ... etc.)
FREQUENCY RANGE	N, SMA, BNC, TNC: 0 - 3000 MHz (or above) MUHF: 0 - 2500 MHz F: 0 - 1500 MHz UHF: 0 - 200 MHz Phono: 0 - 100 MHz
IMPEDANCE	Nom. 50 $\Omega$ (all connector types)
SWR	$\leq 1.5$ for the frequencies stated above (typically $\leq 1.2$ ) See note below
INSERTION LOINS	$\leq 0.5$ for the frequencies stated above (typically $\leq 0.2$ ) See note below
MECHANICAL	
CONTENTS	<b>Two male and two female connector ends of each of the following:</b> N-connector UHF-connector MUHF-connector BNC-connector TNC-connector SMA-connector F-connector Phono-connector Eight connector joints
MATERIAL	Gold-plated brass Teflon insulation
DIMENSIONS	Soft case: 190 mm x 120 mm x 30 mm Coaxial adapter: Approx. 53 mm x 16 mm dia. (N: 20 mm dia, UHF: 17 mm dia.)
WEIGHT	Complete set (case): Approx. 680 g

### PLEASE NOTE

The specifications for SWR and insertion loss are given for a "complete" adapter (same connector type at each end), ie. two connector ends and one connector joint.



PROCOM A/S reserve the right to amend specifications without prior notice.

07/12/11